


On-Loom Reed Cleaner for Air Jet Looms **TR-7600RC**



Brush

The TR-7600RC automatically cleans the groove of a reed on the AJL with the warp yarn still drawn in. Debris build up in the tunnel groove can affect air flow, but is effectively removed with special brushes contributing to stable loom operation.

- Re-chargeable power source makes easier cleaning possible with the cordless unit.
- Special brushes effectively remove the build-up of debris which tends to gather due to the air pressure dynamics in the tunnel groove.
- The unit can be preset to stop after the desired number of cleaning cycles.



Repeat cycle setting



Completion of Cleaning

SPECIFICATIONS

Model	TR-7600RC
Mechanism	Special Brush Rotation (Moving along tunnel groove, left and right repeatedly)
Available Air Jet Loom Makers	All AJL Makers: Brush position adjustable depending on tunnel groove position. 【On Picanol AJL, at least 107mm space is required above the vertical position reed.】
Rotating Brush Component/Traveling Speed	1600 rpm (right and left reversible spin) / Approximately 50 cm/min
Rotating Brush Materials	Horse Hair
Power Source	Rechargeable, 100 V - 240 V Single Phase
Time required for full recharging	About 8 hours
Max. Cleaning time at full recharged	About 8 hours
Dimensions	210mm×160mm×113mm
Weight	2.5Kg

TAKAYAMA REED CO.,LTD.

2-27-20 JINGUJI, KANAZAWA, ISHIKAWA 920-0806 JAPAN

TEL: +81-76-252-2266

<https://www.takayamareed.co.jp/en/>

E-mail: info@takayamareed.co.jp

